



## Thermaheat - Master 415 Volt 9 KW 16 Amp 5 Pin Electric Fan Heater



### Unit Specification:

|  |                                   |
|--|-----------------------------------|
| Voltage :                              | 415 Volt (3 Phase)                |
| Powercord (400 Volt) :                 | Optional Extra                    |
| Heat Settings (Fixed) :                | 2                                 |
| Heating Power (Kw) Positions 3 & 4 :   | 4.5 Kw & 9.0 Kw                   |
| Heating Power (Btu) Positions 3 - 4 :  | 15,350 Btu Variable To 30,700 Btu |
| Heating Power (Kcal) Positions 3 - 4 : | 3,870 Kcal Variable To 7,740 Kcal |
| Cooling Fan Settings Position 2 :      | 1                                 |
| Input Plug (Heater Side) :             | 16 Amp                            |
| Thermostat Control (Analog) :          | Not Available                     |
| Thermostat Control (Digital) :         | Not Available                     |
| Air Displacement :                     | 800 M3/h                          |
| Working Temperature Range :            | 5 > 35 Degrees C                  |
| Fan Type :                             | Axial                             |
| Power Fan Motor :                      | 16 - 52 Watts                     |
| Rated Current :                        | 13 Amp                            |
| Motor Thermal Protection :             | Included                          |
| Overheat Thermostat Protection :       | Included                          |
| Length :                               | 34.0cm                            |
| Width :                                | 42.0cm                            |
| Height :                               | 44.0cm                            |
| IP Rating :                            | IP24                              |
| Trolley Wheel Kit :                    | Not Available                     |
| Noise Level :                          | 55 dB(A)                          |
| Weight :                               | 10kg                              |